





Version: 001-2012



DE Im Ruhezustand
EN In idle state
FR En veille
IT In riposo
NL In standby-stand
ES Modo inactivo
PT No descanso
DK I hviletilstand
SE I vänteläge
FI Joutotilassa
NO I hviletilstand
PL W stanie spoczynku
CZ V klidovém stavu
RU в режиме покоя



DE Während des Gesprächs
EN During call
FR Pendant la communication
IT In conversazione
NL Tijdens gesprek
ES Durante la llamada
PT Durante uma chamada
DK Under opkaldet
SE Under pågående samtal
FI Puhelun aikana
NO Under samtalen
PL W trakcie rozmowy
CZ Během hovoru
RU во время вызова

EN	Icons
	New missed calls
	Speaker on
	Microphone on (hands-free)
	Handset active (handset off-hook)
	New message waiting
	Ring-back initiated
	Number presentation switched off
	Headset on
	Call diversion activated
	Phone locked, can only be unlocked with PIN
	Encrypted telephone connection
	Ringtone off
	Registration successful
	Registration failed
	Registration on stand-by system

EN Short user guide innovaphone IP222 / IP232

This user guide is for both the IP222 and IP232 telephones. For the IP232 telephone, both the menu/OK key and the touch display can be used to activate a telephone function. The IP232 function keys are also available using the touch screen.

Display components (see numbering on illustrations)

- 1 Name of active registration
- 2 Own extension number
- 3 Contact field
- 4 Display icons 1
- 5 Date and time
- 6 Display icons 2

Key functions

Key	In idle state	During call
Disconnect 	Exit menu, return to home screen	Terminates call
Microphone 	Switches ringing tone off	Mute / mute key switches microphone off
R key 	Displays in-bound call list, deletes last character in editor mode	Sets up a consultation call, switches between two calls
Redial 	Displays out-bound call list	Forwards the incoming call or active call
Speaker 	Prepares call, picking up a call in hands-free mode	Listen-in, switch to hands-free mode
Menu, 4-direction navigation key 	Menu key in the middle opens the menu and confirms the selection made, four direction control key to navigate in menu	Left and right key to adjust volume, menu key to set up conference with two active calls
Escape 	One level back in menu	Disconnect call

Actions for incoming calls

Accept call: Pick up handset, press to pick up call in hands-free mode.

Reject call: Press .

Call diversion: Press before accepting the call, enter telephone number for the call diversion and confirm by pressing again.

Actions in idle state

Dialling: Enter telephone number; to dial by name, long press to change to characters and enter name, use down key to select desired name if necessary, pick up handset to initiate call.

Call completion on missed call: Press , if necessary press down key to select desired call, pick up handset to initiate call.

Re-dial: Press , select entry with down key if necessary and pick up handset to initiate call.

Send message: Enter telephone number or name, press menu key in the centre, select send message and enter the desired text, send by pressing menu key.

Set call diversion: Press menu key, select user setup, select call diversion by entering the target number under the required condition. Press then the menu key to save the setting.

Set presence: Press menu key, select user setup and presence. Set required activity and add note as necessary.

Actions during call

Change to hands-free: Keep pressed and hang up.

Terminate hands-free: Pick up handset or terminate call by pressing .

Consultation: Press , select number or name for consultation call. Terminate consultation with and return to initial call.

Switch between calls: Press and set up second call. Double press to switch between calls. Press to terminate calls.

Transfer: Press and set up second call. Hang up to connect the two calls to each other.

Conference: Set up two calls using the key and switch to conference with menu key. Press menu key again to separate calls or hang up to terminate.

Quick transfer: Press and dial target number required. If you hang up before the call is initiated, the caller will hear the ring-tone until the person being called picks up the call.

Blind transfer: Press and set up second call. Press once more to connect calls together without the callers being put in the wait queue.

Actions when initiating a call

Call completion on busy subscriber: Initiate call, press the menu key when you hear busy tone or call waiting signal, then select recall. The telephone will indicate when the subscriber is available again.

Call completion on no reply: Initiate call, press the menu key while hearing the ring tone, and select recall. The telephone will indicate when the subscriber is active again.

Icons in contact field

Icon	Meaning	Icon	Meaning
	Call pending		Presence icon: lunch
	Call initiated, ringing		Presence icon: meeting
	Connected, conference, wait queue		Presence icon: away
	Presence icon: vacation		Presence icon: busy